

ZONE Series

ZONE-120M / ZONE-240M / ZONE-360M / ZONE-480M / ZONE-600M



Features

- ⇒ High sensitivity digital tuner for clear sound.
- ⇒ Memorizing function for radio frequency.
- ⇒ MIC/LINE 1~4 and LINE 5~6 with individual volume controller.
- ⇒ Priority function for mic, chime, siren, or remote.
- ⇒ Able to play the MP3 files stored in USB or SD card
- ⇒ Able to record the broadcast and save into USB or SD card.
- ⇒ 4 tones of chime for the beginning and end of the broadcast.
- ⇒ Siren button for manual operation.
- ⇒ Telephone paging for remote broadcast.
- ⇒ Link with remote amp (DRA-9600) for remote broadcast
- ⇒ Link with fire alarm system for automatic emergency broadcast when the signal is in.
- ⇒ Protection circuit and fan is embedded in case of overheat.
- ⇒ Able to turn on or off the power remotely.
- ⇒ Battery connector on the rear for connecting DC24V battery.

Specification

	ZONE-120M	ZONE-240M	ZONE-360M	ZONE-480M	ZONE-600M
Rated Power	120W	240W	360W	480W	600W
Frequency Response	80Hz ~ 18KHz				
T.H.D	≤ 1%				
S/N	MIC1~4 : ≥ 55dB / LINE1~6 : ≥ 70dB				
Tone Control (±10dB)	100Hz, 10KHz				
REC OUT	1V / 3kΩ, UNBAL				
PRE OUT	1V / 100Ω, UNBAL				
Power Consumption	350W	630W	1160W	1500W	1700W
Weight	13kg	14kg	19kg	21kg	22kg
Dimension	420 × 132 × 380				